

Hydroblaster Pressure Washer

5/5000 EHG V - Electric Motor, Hot Water Pressure Washer

Hydroblaster 5/5000EHGV high-pressure hot water systems provide flow of 5GPM with variable pressure up to 5000PSI. All EHG V systems can be configured for natural gas or propane heating operation. Systems employ high efficiency motors compatible with various electrical supply voltage for either 60Hz or 50Hz operation. All EHG V model Hydroblaster pressure washers are certified to UL-1776, CSA, and conform to CE standards.

Standard Features

- 208/230 Volt
- Hinged Access Equipment Enclosure
- Premium Efficiency Drive Motor
- Belt Driven Pump
- Schedule 80 Coil With Extended Warranty
- Draft Diverter
- Automatic System Shut Down Timer
- Automatic Burner Ignition and Controls
- Trigger Gun System Discharge Control
- Discharge Soap/Chemical Injection
- Dual Nozzle Variable Pressure Wand

Optional Features

- Suitable For a Variety of Power Supplies Including 50Hz
- Power Vent Burner Exhaust
- Lockable Power Disconnect Switch
- Hour Meter, Pressure and Temperature Gauges
- Trigger Actuated Start
- Remote Control Station In NEMA 4X Enclosures
- Stainless Trim: Pump Enclosure and Coil Housing
- Nozzle Options including Turbo Nozzle
- Precision (Peristaltic Pump) Inlet Soap
- Soap Injection Flow Meter
- Plastic Float Tank
- Fresh/Recycle Water Supply w/Motorized Ball Valve
- Hose Reels
- HP Hose, Various Lengths



Pricing

For complete pricing details,
Submit a quote online below.

[Get a Quote](#)



Hydroblaster Pressure Washer

5/5000 EHG V - Electric Motor, Hot Water Pressure Washer

Specifications

Volume - GPM (LPM)	5 (18.9)
Pressure - PSI (BAR)	5000 (345)
BTU Minimum Supply	400000
Exhaust Diameter - Inch (mm)	10 (254)
Electric Motor - HP (KW)	20 (14.9)
Dimensions, Inches (cm)	45 (114.3) L X 33 (83.8) W X 55 (139.7) H
Weight, Lbs (kg)	785 (356)
Frame	5BK169 (Sm.)
Coil	20"
Burner	X44

Standard

Volts (60Hz)	230V-3P	460V-3P
Amps (60Hz)	53	27

Pricing

For complete pricing details, Submit a quote online below.

[Get a Quote](#)

